

Ruttonsha International Rectifier Ltd.

**POWER MODULES** 

IRK. 26 Series High Voltage Thyristor/ Diode and Thyristor/ Thyristor

# **FEATURES**

# Electrically isolated base plate.
# 3500Vrms isolated voltage.
# Simplified mechanical designs, rapid assembly.
# Auxiliary cathode terminal for wiring convenience.
# High surge capability.
# Wide choice of circuit configuration.
# Large creepage distance.



## DESCRIPTION

These IRK series of Power Modules use power diodes and thyristor in a variety of circuit configuration. The semiconductors chips are electrically isolated from the metal base, allowing common heat sinks and compact assemblies to be built. They can be interconnected to form single phase or three phase bridges or AC controller. These modules are intended for general purpose applications such as regulated power supplies. lighting circuits and temperature and motor speed control circuit.

### **MAJOR RATING & CHARACTERISTICS**

Parameters		IRK. 26	Units
IT(AV)	@Tc-85°C	27	А
O(RMS)		42	А
FSM	@ 50Hz	400	A
l <sup>2</sup> t	@ 50Hz	800	A²s
VRRM		400 to 1600	V
Тѕтб		-40 to 125	°C
T,		-40 to 125	°C

# IRK. 26 Series

# ELECTRICAL SPECIFICATION VOLTAGE RATINGS

Type Number	Voltage Code	VRMM max. repetitive peak reverse and off-state blocking voltage V	V <sub>RSM</sub> max.Non-repetitive peak reverse voltage V	IDRM / IRRM Max. @ 150°C Max. mA
	04	400	500	
	06	600	700	
IRK.26	08	800	900	15
	10	1000	1100	15
	12	1200	1300	
	14	1400	1500	
	16	1600	1700	

## **ON-STATE CONDUCTION**

L

	Parameter	IRK. 26	Unit	Conditions			
I <sub>T(AV)</sub>	Max, average On-state current (Thyristors)	27	A	180°C conduction, half sine wave Tc = 85°C			
I <sub>F(AV)</sub>	Max, average forward current (Diode)	27	A				
l o(rms)	Max, continuous RMS on-state current	42	A	@ Tc 85	@ Tc 85°C		
I tsm or I fsm	Max, peak, one cycle non-repetitive on-state or forward current	400	A	t = 10ms	Sinusodial half wave initial Tj = Tj max.		
l²t	Maximum I <sup>2</sup> t for fusing	800	A²s	t = 10ms			
		1100	A <sup>2</sup> s	t = 10ms Tj = 25°C			
V <sub>T(TO)</sub>	Max, value of Threshold voltage	0.95	V	Tj = Tj max.			
rt	Max, value of on-state slope resistance	40	mΩ	Tj = Tj max,			
VTM	Max, peak on-state voltage	1.95	V	$I_{TM} = \pi \times I_{T(AV)} \qquad TJ = 25^{\circ}C \\ 180^{\circ} \text{ conduction}$			
di/dt	Max, non-repatitive rete of rise of turned on current	100	A/µs	Tj = 25°C from. 0.67V <sub>DRM</sub> Ιτ <sub>Μ</sub> = π x Ιτ <sub>(AV)</sub> , Ig =500mA t <sub>r</sub> < 0.5μs, t <sub>P</sub> >6μs			
Iн	Maximum holding current	200	mA	Tj = 25°C. anode supply = 6V resistive load. gate open circuit			
l.	Max, latching current	400	mA	Tj = 25°C, anode supply = 6V. resistive load			

٦

# POWER MODULES

# IRK. 26 Series

## ELECTRICAL SPECIFICATION TRIGGERING

	Parameter	IRK. 26	Unit	Conditions	
Р <sub>бм</sub>	Max, peak gate power	10	w		
P <sub>G(AV)</sub>	Maximum average gate power	2.5			
Ідм	Max, peak gate current	2.5	А		
-V <sub>GM</sub>	Max. peak negative gate voltage	10	V		
V <sub>GT</sub>	Max, gate voltage required to trigger	2.5	V	Tj = 25°C	Anode supply = 6V resistive load
Іст	Max, gate current required to trigger	150	mA	Tj = 25°C	Anode supply = 6V resistive load
V <sub>GD</sub>	Max, gate voltage that will not trigger	0.25	V	Tj = 125°C rated V <sub>DRM</sub> applied	
lgd	Max, gate current that will not trigger	6.0	mA		

### BLOCKING

L

	Parameter	IRK. 26	Unit	Conditions
RRM DRM	Max. peak reverse and off state leakage current at $V_{\text{RM}}$ $V_{\text{DRM}}$	15	mA	Tj = 125°C, gate open circuit
Vins	RMS Isolation voltage	3500	I V	50Hz, Circuit to base, all terminal shorted, t=1 sec.
dv/dt	Max, critical rate of rise of off-state voltage	1000	V/µs	Tj = 125°C linear to 0.67VDRM gate open circuit

## THERMAL AND MECHANICAL SPECIFICATION

	Parameter	IRK. 26	Unit	Conditions
T,	Junction operating temperature range	-40 to 125	°C	
Tstg	Max, storage temperature range	-40 to 125		
RthJ-C	Max, internal thermal resistance junction to case	0.31	°C/W	Per module DC operation
RthCS	Max, thermal resistance, case to heat sink	0.10	°C/W	Mounting surface flat smooth and greased (per Module)
Т	Mounting torque ±10% Busbar to module	5	Nm	A Mounting compound is recommended and the torque should be rechecked after a period of 3 hours to allow for the spread of the compound.
Wt	Approximate Weight	115	g	
	Case style	To-240AA		

٦

# POWER MODULES

IRK. 26 Series

#### OUTLINE DIAGRAM



### CIRCUIT CONFIGURATION TABLE



## CIRCUIT CONFIGURATION TABLE



- 1). Module Type
- 2). Circuit configuration (See Circuit Configuration table)
- 3). Current Code
- 4). Voltage Code (See Voltage Rating Table)